

1 Internet Printing Protocol WG
2 INTERNET-DRAFT
3 <draft-ietf-ipp-job-printer-set-ops-043.txt>
4 Updates: RFC 2910 and 2911
5 [Target Category: standards track]
6 Expires: January 17, 2002

T. Hastings
R. Herriot
Xerox Corporation
Carl Kugler
H. Lewis
IBM Corporation
~~July 17~~ January 22, 2001

7
8
9 **Internet Printing Protocol (IPP):**
10 **Job and Printer Set Operations**

11 Copyright (C) The Internet Society (2001). All Rights Reserved.

12 Status of this Memo

13 This document is an Internet-Draft and is in full conformance with all provisions of Section 10 of
14 [RFC2026]. Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its
15 areas, and its working groups. Note that other groups may also distribute working documents as
16 Internet-Drafts.

17 Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced,
18 or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference
19 material or to cite them other than as "work in progress".

20 The list of current Internet-Drafts can be accessed at <http://www.ietf.org/ietf/1id-abstracts.txt>
21 The list of Internet-Draft Shadow Directories can be accessed as <http://www.ietf.org/shadow.html>.

22 Abstract

23 This document specifies 3 additional OPTIONAL operations for use with the Internet Printing
24 Protocol/1.0 (IPP) [RFC2565, RFC2566], and IPP/1.1 [RFC2911, RFC2910], ~~and future versions~~. The
25 end user, operator, and administrator Set-Job-Attributes and Set-Printer-Attributes operations are used
26 to modify IPP Job objects and Printer objects, respectively. The third administrator Get-Printer-
27 Supported-Values operation returns values that the IPP Printer will accept for setting its "xxx-
28 supported" attributes.

29 Three out-of-band values are defined for use with these operations: 'delete-attribute', 'admin-define',
30 and 'not-settable', along with a 'client-error-attributes-not-settable' status code.

31 Two operation attributes: "printer-message-from-operator" (text) and "job-message-from-operator"
32 (text) are defined to set the corresponding IPP/1.1 Printer and Job Description attributes with the same
33 names.

34 Nine Printer Description attributes are defined:

- 35 printer-settable-attributes-supported (1setOf type2 keyword)
- 36 job-settable-attributes-supported (1setOf type2 keyword)
- 37 document-format-varying-attributes (1setOf type2 keyword)
- 38 printer-message-time (integer(MIN:MAX))

39 printer-message-date-time (dateTime)
40 printer-xri-supported (1setOf collection)
41 xri-uri-scheme-supported (1setOf uriScheme)
42 xri-authentication-supported (1setOf type2 keyword)
43 xri-security-supported (1setOf type2 keyword)
44

44 ~~The full set of IPP documents includes:~~

45 ~~Design Goals for an Internet Printing Protocol [RFC2567]
46 Rationale for the Structure and Model and Protocol for the Internet Printing Protocol [RFC2568]
47 Internet Printing Protocol/1.1: Model and Semantics [RFC2911]
48 Internet Printing Protocol/1.1: Encoding and Transport [RFC2910]
49 Internet Printing Protocol/1.1: Implementer's Guide [IPP-IG]
50 Mapping between LPD and IPP Protocols [RFC2569]~~

51
52 ~~The "Design Goals for an Internet Printing Protocol" document takes a broad look at distributed
53 printing functionality, and it enumerates real-life scenarios that help to clarify the features that need to
54 be included in a printing protocol for the Internet. It identifies requirements for three types of users:
55 end users, operators, and administrators. It calls out a subset of end user requirements that are satisfied
56 in IPP/1.0. A few OPTIONAL operator operations have been added to IPP/1.1.~~

57 ~~The "Rationale for the Structure and Model and Protocol for the Internet Printing Protocol" document
58 describes IPP from a high level view, defines a roadmap for the various documents that form the suite of
59 IPP specification documents, and gives background and rationale for the IETF working group's major
60 decisions.~~

61 ~~The "Internet Printing Protocol/1.1: Encoding and Transport" document is a formal mapping of the
62 abstract operations and attributes defined in the model document onto HTTP/1.1 [RFC2616]. It defines
63 the encoding rules for a new Internet MIME media type called "application/ipp". This document also
64 defines the rules for transporting over HTTP a message body whose Content Type is "application/ipp".
65 This document defines a new scheme named 'ipp' for identifying IPP printers and jobs.~~

66 ~~The "Internet Printing Protocol/1.1: Implementer's Guide" document gives insight and advice to
67 implementers of IPP clients and IPP objects. It is intended to help them understand IPP/1.1 and some
68 of the considerations that may assist them in the design of their client and/or IPP object
69 implementations. For example, a typical order of processing requests is given, including error checking.
70 Motivation for some of the specification decisions is also included.~~

71 ~~The "Mapping between LPD and IPP Protocols" document gives some advice to implementers of
72 gateways between IPP and LPD (Line Printer Daemon) implementations.~~

73

73 **Table of Contents**

74	1 Introduction	7
75	2 Terminology.....	7
76	2.1 Conformance Terminology	7
77	2.2 Other terminology	8
78	3 Requirements and Use Cases	8
79	4 Definition of the Set operations	9
80	4.1 Set-Printer-Attributes Operation.....	9
81	4.1.1 Settable and READ-ONLY Printer Description attributes	11
82	4.1.2 Set-Printer-Attributes Request.....	12
83	4.1.3 Set-Printer-Attributes Response.....	13
84	4.2 Set-Job-Attributes Operation.....	14
85	4.2.1 Settable and READ-ONLY Job Description attributes	16
86	4.2.2 Set-Job-Attributes Request	17
87	4.2.3 Set-Job-Attributes Response.....	17
88	4.3 Get-Printer-Supported-Values Operation.....	18
89	4.3.1 Definition of the usage of the 'admin-define' out-of-band attribute value.....	19
90	5 New Operation attributes	20
91	5.1 printer-message-from-operator (text(127))	21
92	5.2 job-message-from-operator (text(127)).....	22
93	6 New Printer Description Attributes.....	22
94	6.1 printer-settable-attributes-supported (1setOf type2 keyword)	23
95	6.2 job-settable-attributes-supported (1setOf type2 keyword).....	23
96	6.3 document-format-varying-attributes (1setOf type2 keyword).....	23
97	6.4 printer-message-time (integer(MIN:MAX))	23
98	6.5 printer-message-date-time (dateTime).....	24
99	6.6 printer-xri-supported (1setOf collection).....	24
100	6.7 xri-uri-scheme-supported (1setOf uriScheme).....	26
101	6.8 xri-authentication-supported (1setOf type2 keyword)	26
102	6.9 xri-security-supported (1setOf type2 keyword).....	27
103	7 Additional status codes.....	27
104	7.1 client-error-attributes-not-settable (0x0413)	27
105	8 Additional out-of-band values.....	27
106	8.1 'not-settable' out-of-band value	27
107	8.1.1 Encoding of the 'not-settable' out-of-band attribute value.....	28
108	8.2 'delete-attribute' out-of-band value.....	28
109	8.2.1 Encoding of the 'delete-attribute' out-of-band value	28

110	8.3 'admin-define' out-of-band attribute value	28
111	8.3.1 Encoding of the 'admin-define' out-of-band attribute value	29
112	9 New Values for Existing Printer Description Attributes	30
113	9.1 operations-supported (1setOf type2 enum)	30
114	10 Conformance Requirements.....	30
115	11 IANA Considerations	31
116	11.1 Operation Registrations	31
117	11.2 Additional Enum Attribute Value Registrations for the "operations-supported" Printer Attribute.....	32
118	11.3 Attribute Registrations.....	32
119	11.4 Status code Registrations.....	33
120	11.5 Out-of-band Attribute Value Registrations.....	33
121	12 Internationalization Considerations	34
122	13 Security Considerations	34
123	14 Author's Addresses.....	35
124	15 References.....	36
125	16 Appendix A: Allowed Values for Set-Printer-Attributes and Set-Job-Attributes requests	37
126	17 Appendix B: Attributes returned from Get-Printer-Supported-Values	43
127	18 Appendix C: Description of the Base IPP Documents.....	46
128	19 Appendix D: Full Copyright Statement	47

Table of Tables

131	Table 1 - Operation-Id assignments	9
132	Table 2 - Job State Transition Table for the Set-Job-Attributes operation	16
133	Table 3 - Member attributes of "printer-xri-supported" (1setOf collection)	25
134	Table 4 - Operation-id assignments.....	30
135	Table 5 - Validation rules for 'Any of "xxx-supported" '	37
136	Table 6 - Validation rules for 'From Get-Printer-Supported-Values'	38
137	Table 7 - Values allowed for Job Template Attributes in the Set-Job-Attributes Operation.....	39
138	Table 8 - Values allowed for Job Description Attributes in the Set-Job-Attributes Operation	40
139	Table 9 - Values allowed for Printer Job Template Attributes in the Set-Printer-Attributes Operation.....	41
140	Table 10 - Values allowed for Printer Description Attributes in the Set-Printer-Attributes Operation	42
141	Table 11 - Printer Job Template Attributes returned from Get-Printer-Supported-Values.....	44
142	Table 12 - Printer Job Template Attributes returned from Get-Printer-Supported-Values.....	44
143	Table 13 - Printer Description Attributes returned from Get-Printer-Supported-Values.....	44
144	Table 14 - Printer Job Template Attributes returned from Get-Printer-Supported-Values.....	44

145 Table 15 - Printer Job Template Attributes returned from Get-Printer-Supported-Values..... 45
146 Table 16 - Printer Description Attributes returned from Get-Printer-Supported-Values..... 46
147
148
149

149

1 Introduction

150

This document is an **OPTIONAL** extension to IPP/1.0 [RFC2565, RFC2566] and IPP/1.1 [RFC2911, RFC2910], ~~and future versions.~~ For a description of the base IPP documents see section 18.

151

152

The Internet Printing Protocol (IPP) is an application level protocol that can be used for distributed printing using Internet tools and technologies. IPP version 1.1 [RFC2911, RFC2910] focuses on end user functionality with a few administrative operations included. This document defines additional **OPTIONAL** end user, operator, and administrator Set-Job-Attributes and Set-Printer-Attributes operations used to modify IPP Job objects and Printer objects, respectively. It also defines a third ~~administrator~~ Get-Printer-Supported-Values **administrator** operation that returns values that the IPP Printer will accept for setting its "xxx-supported" attributes. The Get-Printer-Supported-Values operation **MUST** be supported, if the implementation supports setting any "xxx-supported" Printer attributes using the Set-Printer-Attributes operation.

153

154

155

156

157

158

159

160

161

Three out-of-band values are defined for use with these three operations: 'delete-attribute' for deleting Job attributes with the Set-Job-Attributes request, 'not-settable' for use in either the Set-Job-Attributes or Set-Printer-Attributes responses, and 'admin-define' for use in the Get-Printer-Supported-Values response.

162

163

164

165

Two operation attributes: "printer-message-from-operator" (text) and "job-message-from-operator" (text) are defined to set the corresponding IPP/1.1 Printer and Job Description attributes with the same names. These operation attributes may be used with any operation that affect the Printer or Job object for which an operation might want to indicate a message. For the Set-Job-Attributes and Set-Printer-Attributes operations, the client **MUST** explicitly set them, rather than using these operation attributes.

166

167

168

169

170

A Printer implementation can make the value of some attributes dependent on the document-format, e.g. "resolution-supported".

171

172

2 Terminology

173

This section defines terminology used throughout this document.

174

2.1 Conformance Terminology

175

Capitalized terms, such as **MUST**, **MUST NOT**, **REQUIRED**, **SHOULD**, **SHOULD NOT**, **MAY**, **NEED NOT**, and **OPTIONAL**, have special meaning relating to conformance. ~~These terms are defined in [RFC2911] section 12.1 on conformance terminology, most of which is taken from as defined in RFC 2119 [RFC2119] and [RFC2911] section 12.1. If an implementation supports the extension defined in this document, then these terms apply; otherwise, they do not. These terms define conformance to this document only; they do not affect conformance to other documents, unless explicitly stated otherwise.~~

176

177

178

179

180

181

182

~~The following specialization of these terms apply to this document:~~

183 ~~REQUIRED: if an implementation supports the extensions described in this document, it MUST~~
184 ~~support a REQUIRED feature.~~
185 ~~OPTIONAL: if an implementation supports the extensions described in this document, it MAY support~~
186 ~~an OPTIONAL feature.~~

187 2.2 Other terminology

188 This document uses terms such as Job object (or Job), IPP Printer object (or Printer), "operation",
189 "request", "response", "attributes", "keywords", and "support". These terms have special meaning and
190 are defined in the model terminology [RFC2911] section 12.2. The following additional terms are
191 introduced in this document:

192 READ-ONLY: used in an attribute definition document to indicate that the attribute MUST NOT be
193 settable using an IPP protocol Set operation. In other words, the attribute is not settable by
194 definition.

195 not-settable: an implementation does not support setting an attribute (whether or not the attribute's
196 definition is READ-ONLY).

197 3 Requirements and Use Cases

198 The following requirements and usage are intended to be met by the specification in this document.

- 199 1. The end-user and the operator need a way to modify a Job that is in the 'pending' or 'pending-held'
200 state.

201 Usage: The end-user discovers that he/she forgot to include a print instruction, such as "finishings"
202 = 'staple' after submitting a job. Rather than canceling the job and resubmitting it to the same IPP
203 Printer, the end-user is able to modify the job on the IPP Printer.

204 The operator needs to modify a job because it is requesting a particular kind of media for which
205 there is no more, but the policy is to print the job on a comparable medium.

- 206 2. The system administrator needs a way to re-configure or change the policy of the IPP Printer
207 remotely.

208 Usage: The system administrator is adding additional named media to the supported media list
209 (setting 'name' values to the "media-supported" Printer attribute).

210 The system administrator is reducing the capability of the IPP Printer by removing one of the
211 operations from the supported operations list, such as Cancel-Job, because the policy is to run the
212 IPP Printer like a public facsimile machine. After having removed Cancel-Job from the list of
213 supported operations, an administrative client needs to be able to display to an administrator that
214 the implementation is capable of being reconfigured to support Cancel-Job once again.

215 The system administrator is remotely configuring the IPP Printer after installing it, and so is
 216 replacing the Printer Description attributes that have the out-of-band 'no-value' value (see
 217 [RFC2911] section 4.1) with the proper values.

218 The operator is changing the media loaded in the input tray and so is replacing the "media-ready"
 219 Job Template Printer attribute value with the proper values

220 4 Definition of the Set operations

221 The Set-Printer-Attributes operation (as are all Printer operations) are directed at Printer objects. A
 222 client **MUST** always supply the "printer-uri" operation attribute in order to identify the correct target of
 223 the operation. These descriptions assume all of the common semantics of IPP/1.1 Model and Semantics
 224 document [RFC2911] section 3.1.

225 The Set-Job-Attributes operation (as are all Job operations) are directed at Job objects. A client **MUST**
 226 always supply some means of identifying the Job object in order to identify the correct target of the
 227 operation. That job identification **MAY** either be a single Job URI or a combination of a Printer URI
 228 with a Job ID as defined in [RFC2911]. The IPP object implementation **MUST** support both forms of
 229 identification for every job. If possible, a client **SHOULD** use the Printer URI with a Job ID rather than
 230 a Job URI, since the 32-bit "job-id" is more readily translated to and from other print protocols that
 231 **MAY** be serving as gateways into or out of the IPP implementation.

232 The Set Printer operations are summarized in Table 1:

233 **Table 1 - Operation-Id assignments**

Operation Name	Operation-Id	Brief description
Set-Printer-Attributes	0x0013	Sets attribute values of the target Printer object
Set-Job-Attributes	0x0014	Sets attribute values of the target Job object
Get-Printer-Supported-Values	0x0015	Gets values that are valid for setting "xxx-supported" attributes using the Set-Printer-Attributes operation

234 4.1 Set-Printer-Attributes Operation

235 This **OPTIONAL** operation allows a client to set the values of the attributes of a Printer object. In the
 236 request, the client supplies the set of Printer keyword attribute names and values that are to be set. In
 237 the response, the Printer object returns success or rejects the entire request with indications of which
 238 attribute or attributes could not be set.

239 The Printer object validates the client-supplied attributes in the Set-Printer-Attributes request. For an
 240 attribute to validate it **MUST** meet all of the following rules:

241 1. The number of attributes supplied by the client MUST NOT exceed the maximum number that the
242 Printer supports in a Set-Printer-Attributes request. A Printer MUST accept at least one attribute,
243 but SHOULD accept a reasonable number in a single Set-Printer-Attributes request.

244 Note: There is no way for the client to determine the maximum number of attributes that the
245 Printer supports in a Set-Printer-Attributes request, except to try a reasonable number.

246 2. The Printer MUST support the attribute.

247 3. The attribute MUST NOT be READ-ONLY, i.e., the definition of the attribute MUST NOT
248 indicate that the attribute is READ-ONLY (see Appendix A for an indication of which IPP/1.1
249 attributes are READ-ONLY).

250 4. The attribute MUST be settable in this implementation.

251 5. The Printer MUST support the value according to the rules defined in Appendix A, i.e., each value
252 of each supplied "xxx" attribute MUST be validated against a value of a corresponding "xxx-
253 supported" Printer attribute. One of those rules permits an administrator to set arbitrary 'name'
254 values to those "xxx-supported" Printer attributes that include the 'name' attribute syntax if the
255 implementation supports the 'admin-define' out-of-band value for that "xxx-supported" attribute
256 (see section 16 and 8.3).

257 6. The attribute's values MUST NOT conflict with the values of other Printer attributes, including
258 ones being set in this same operation.

259 If any of the supplied attributes does not validate, the Printer object MUST reject the entire operation;
260 the Printer object MUST NOT partially set some of the supplied attributes. In other words, after the
261 operation, all the supplied attributes MUST be set or none of them MUST be set, thus making the Set-
262 Printer-Attributes an atomic operation.

263 The Printer MUST accept this operation when its READ-ONLY "printer-state" attribute (see
264 RFC2911] section 4.4.11) is 'idle' or 'stopped', and SHOULD accept it when the value is 'processing'.
265 The Printer MUST accept this operation for any of the values of the Printer object's READ-ONLY
266 "printer-state-reasons" and "printer-is-accepting-jobs" attributes, unless explicitly defined otherwise in
267 the definition of these attributes' values.

268 This operation MUST NOT change the value of attributes not specified in the operation unless the
269 definition of the attribute explicitly specifies such side-effects. For example, this document explicitly
270 specifies that when this operation sets "printer-message-from-operator", the Printer also MUST set the
271 READ-ONLY "printer-message-time" and READ-ONLY "printer-message-date-time" attributes to the
272 time of the operation as a side effect. In particular, if this operation changes an "xxx-default" attribute,
273 the new value MUST be in the "xxx-supported" attribute or the request MUST contain a new value for
274 "xxx-supported" which contains the new value for the "xxx-default". Otherwise, the Printer MUST
275 reject the operation. In general, Printer attribute definitions that are settable will not define side-effects
276 on other attributes that are settable, only side effects on READ-ONLY attributes, if any.

277 4.1.1 Settable and READ-ONLY Printer Description attributes

278 If the Printer supports the Set-Printer-Attributes operation, then it SHOULD support setting of:
279 all Job Template Default ("xxx-default") attributes
280 all Job Template Supported ("xxx-supported") attributes
281 all Job Template Ready ("xxx-ready") attributes
282 that the implementation supports (see [RFC2911] section 4.2 and extensions).

283 Some Printer Description attributes (see [RFC2911] section 4.4) MUST NOT be settable, i.e., they are
284 defined to be READ-ONLY. An attribute marked as "READ-ONLY" in the Printer Description
285 attribute table in Appendix A is such an attribute. The Printer attributes that are not marked as "READ-
286 ONLY" MAY be settable using the Set-Printer-Attributes operation, depending on implementation.

287 Note: From now on, all extensions that define new object attributes will indicate whether or not the
288 attributes are READ-ONLY, by including the "READ-ONLY" adjective in their descriptions and/or
289 explicitly stating whether they MAY be settable.

290 The current values of each "xxx-supported" Printer attribute MUST reflect the current policy for
291 support of the corresponding "xxx" attribute. If an "xxx-supported" Printer attribute is settable in an
292 implementation, then its value(s) MUST affect the behavior of the implementation. If an "xxx-
293 supported" Printer attribute is defined to be READ-ONLY or is not-settable in an implementation, then
294 its values MUST NOT be settable using the Set-Printer-Attributes operation. Consider the following
295 example:

296 For example, if the "operations-supported" Printer Description attribute (see [RFC2911] section
297 4.4.15) is settable in a particular implementation, then changing its value with a Set-Printer-
298 Attributes operation MUST affect the operations that the implementation accepts or rejects. Such an
299 implementation will need to be able to reject values for operations that it contains no code support
300 for (see section 4.3). If the "operations-supported" Printer Description attribute is not settable in a
301 particular implementation, then that implementation MUST reject an attempt to set it with a Set-
302 Printer-Attributes operation, return the 'client-error-attributes-not-settable' status code (see section
303 7.1), and return the "operations-supported" attribute with the out-of-band 'not-settable' value in the
304 Unsupported Attributes Group.

305 As another example, consider an implementation in which the "media-default" and "media-
306 supported" are settable. If a client supplies a Set-Printer-Attributes request that contains the "media-
307 default" attribute with a value that is not a member of the Printer's "media-supported" attribute, the
308 Printer MUST reject the request and return the "client-error-conflicting-attributes" status code with
309 the "media-default" and "media-supported" attributes and their values (see [RFC2911] section 3.1.7).

310 As a third example, if a client supplies a Set-Printer-Attributes request that contains both the "media-
311 default" and the "media-supported" attributes, but includes a value in the "media-default" that is not a
312 member of the supplied "media-supported" attribute, the Printer MUST reject the request and return
313 the "client-error-conflicting-attributes" status code with the "media-default" and "media-supported"
314 attributes and their values (see [RFC2911] section 3.1.7).

315 *Access Rights:* The authenticated user (see [RFC2911] section 8.3) performing this operation must be
316 an operator or administrator of the Printer object (see [RFC2911] Sections 1 and 8.5). Most Printer
317 attributes will require administrator access rights to set, such as "xxx-supported", while some will
318 require operator access rights only, such as "media-ready" and "printer-message-from-operator". Which
319 attributes require which access rights depends on implementation and MAY depend on site policy.

320 **4.1.2 Set-Printer-Attributes Request**

321 The following sets of attributes are part of the Set-Printer-Attributes Request:

322 Group 1: Operation Attributes

323 Natural Language and Character Set:

324 The "attributes-charset" and "attributes-natural-language" attributes as described in [RFC2911]
325 section 3.1.4.1.

326 Target:

327 The "printer-uri" (uri) operation attribute which is the target for this operation as described in
328 [RFC2911] section 3.1.5.

330 Requesting User Name:

331 The "requesting-user-name" (name(MAX)) attribute SHOULD be supplied by the client as
332 described in [RFC2911] section 8.3.

334 "document-format" (mimeMediaType):

335 The client OPTIONALLY supplies this attribute. The Printer object MUST support this
336 attribute. This attribute is useful for a client to select the document-format to which the
337 attribute modification should be applied. A Printer implementation MAY allow some
338 attributes to have different values for each document format that it supports. See [RFC2911]
339 section 3.2.5.1 "Get-Printer-Attributes Request".

341
342 If the client includes this attribute, the Printer MUST change the supplied attributes for the
343 document format specified by this attribute. If a supplied attribute is a member of the
344 "document-format-varying-attributes" (i.e., the attribute varies by document format, see
345 section 6.3), the Printer MUST change the supplied attribute for the document format specified
346 by this attribute, but not for other document formats. If a supplied attribute isn't a member of
347 the "document-format-varying-attributes" (i.e. it doesn't vary by document format), the Printer
348 MUST change the supplied attribute for all document formats.

349
350 If the client omits this attribute, the Printer MUST change the supplied attributes for all
351 document formats whether or not they vary by document-format.

352
353 If the client supplies a value for the "document-format" Operation attribute that is either
354 'application/octet-stream' or not supported by the Printer, i.e., is not among the values of the
355 Printer object's "document-format-supported" attribute, the Printer object MUST reject the

356 operation and return the 'client-error-document-format-not-supported' status code. Note: the
357 document-format 'application/octet-stream' is the union of several document-formats (see
358 [RFC2911] section 3.2.5.1, Get-Printer-Attributes) and is not a true document-format.
359

360 Group 2: Printer Attributes

361 The client MUST supply a set of Printer attributes with one or more values (including
362 explicitly allowed out-of-band values) as defined in [RFC2911] section 4.2 Job Template
363 Attributes ("xxx-default", "xxx-supported", and "xxx-ready" attributes), section 4.4 Printer
364 Description Attributes, and any attribute extensions supported by the Printer. The value(s) of
365 each Printer attribute supplied in Group 2 replaces the value(s) of the corresponding Printer
366 attribute on the target Printer object. For attributes that can have multiple values (1setOf), all
367 values supplied by the client replace all values of the corresponding Printer object attribute. If
368 a Printer object attribute had not been configured yet and so had the 'no-value' out-of-band
369 value (see [RFC2911] section 4.1), the supplied value(s) replace the 'no-value' value.
370

371 4.1.3 Set-Printer-Attributes Response

372 The Printer object returns the following sets of attributes as part of the Get-Printer-Attributes
373 Response:

374 Group 1: Operation Attributes

375 Status Message:

376 In addition to the REQUIRED status code returned in every response, the response
377 OPTIONALLY includes a "status-message" (text(255)) and/or a "detailed-status-message"
378 (text(MAX)) operation attribute as described in [RFC2911] sections 13 and 3.1.6.
379

380 Natural Language and Character Set:

381 The "attributes-charset" and "attributes-natural-language" attributes as described in [RFC2911]
382 section 3.1.4.2.
383

384 Group 2: Unsupported Attributes

385 See [RFC2911] section 3.1.7 for details on returning Unsupported Attributes.
386

387 If some of the attributes in the operation fail to validate, the Printer MUST reject the
388 operation, MUST NOT change any Printer attributes, and MUST return the indicated status
389 code below. In this group, the Printer MUST also return all attributes that fail to validate.
390 The following are the reasons that an attribute fails to validate and the value returned for the
391 attribute, along with the indicated status code and order of detection:
392

- 393 1. The number of attributes supplied by the client exceeds the maximum number that the
394 Printer supports in a Set-Printer-Attributes request: return the 'client-error-request-entity-
395 too-large' (see [RFC2911] section 13.1.4.9).

- 396 2. The Printer doesn't support the attribute: return the attribute with the "out-of-band" value
397 'unsupported' (see [RFC2911] section 3.1.7 and [RFC2910]) and the 'client-error-
398 attributes-or-values-not-supported' (see [RFC2911] section 13.1.4.12).
- 399 3. The attribute is either READ-ONLY (in its definition) or is not-settable in this
400 implementation: return the attribute with the "out-of-band" value 'not-settable' (see section
401 8.1) and the 'client-error-attributes-not-settable' status code (see section 7.1).
- 402 4. The Printer doesn't support the value: if the attribute in the operation has a single value
403 return it. If the attribute in the operation is multi-valued, return only those values in a
404 1setOf that are not supported. Return the 'client-error-attributes-or-values-not-supported'
405 status code (see [RFC2911] section 13.1.4.12).
- 406 5. The values of some of the supplied attributes conflict with one another and/or other Printer
407 attribute values not being set: if the conflicting attribute in the operation has a single value
408 return the attribute and the value. If the attribute in the operation is multi-valued, return
409 only the attribute and those values in a 1setOf that are conflicting with other attributes.
410 Return the 'client-error-conflicting-attributes' status code (see [RFC2911] section
411 13.1.4.15).

412 **4.2 Set-Job-Attributes Operation**

413 This OPTIONAL operation allows a client to set the values of the attributes of a Job object. In the
414 request, the client supplies the set of Job keyword attribute names and values that are to be set. In the
415 response, the IPP object returns success or rejects the entire request with indications of which attribute
416 or attributes could not be set.

417 This operation is almost identical to the Set-Printer-Attributes operation and follows the same rules for
418 validation (see section 4.1). The only differences are that the Set-Job-Attributes operation is directed at
419 a Job object rather than a Printer object, there is no "document-format" operation attribute used when
420 setting a Job object, the operation can add an attribute to the (Job) object, the 'delete-attributes' out-of-
421 band value is permitted to remove an attribute, and the validation is the same as the Job Creation
422 operations (Print-Job, Print-URI, and Create-Job), i.e., depends on the "xxx-supported" Printer
423 Description attributes (see [RFC2911] section 3.1). Using the Set-Printer-Attributes operation, the
424 administrator can set arbitrary 'name' values to those "xxx-supported" Printer attributes that include the
425 'name' attribute syntax if the implementation supports the 'admin-define' out-of-band value for that "xxx-
426 supported" attribute (see section 16 and 8.3). However, the Set-Job-Attributes cannot be used to add
427 unsupported names to the Job object.

428 If a client supplies a job attribute in a Set-Job-Attributes request that the Printer supports, and the job
429 was originally submitted without supplying that attribute, the Printer adds the attribute to the Job object.

430 If the client supplies a job attribute with the "out-of-band" value 'delete-attribute' (see section 8.2), then
431 the Printer MUST remove the attribute and all of its values from the Job object, if present. The
432 semantic effect of the client supplying the 'delete-attribute' value in a Set-Job-Attributes operation
433 MUST be the same as if the attribute had not been supplied with the Job object in the Job Creation

434 operation, i.e., the Printer applies its default attribute or behavior with lower precedence than the PDL
435 (see the beginning of [RFC2911] section 4.2 and [RFC2911] 3.2.1.1). Any subsequent query of the Job
436 object using Get-Job-Attributes or Get-Jobs MUST NOT return any attribute that has been deleted
437 using the 'delete-attribute' out-of-band value. However, a client can re-establish such a deleted Job
438 attribute with any supported value(s) using a subsequent Set-Job-Attributes operation.

439 If the client supplies an attribute in a Set-Job-Attributes request with the 'delete-attribute' value and that
440 attribute is not present on the Job object, the Printer ignores that supplied attribute in the request, does
441 not return the attribute in the Unsupported Attributes group, and returns the 'successful-ok' status code,
442 if there are no other problems with the request.

443 The validation of the Set-Job-Attributes request is performed by the Printer as if the job had been
444 submitted originally with the new attribute values (and the deleted attributes removed) and with "ipp-
445 attribute-fidelity" set to 'true', i.e., all modified attributes Job attributes and values MUST be supported
446 in combination with the Job attributes not modified. If such a Job Creation operation would have been
447 accepted, then the Set-Job-Attributes MUST be accepted. If such a Job Creation operation would have
448 been rejected, then the Set-Job-Attributes MUST be rejected and the Job MUST be unchanged. In
449 addition, if any of the supplied attributes are not supported, are not settable, or the values are not
450 supported, the Printer object MUST reject the entire operation; the Printer object MUST NOT partially
451 set some of the supplied attributes. In other words, after the operation, all the supplied attributes
452 MUST be set or none of them MUST be set, thus making the Set-Job-Attributes an atomic operation.

453 The IPP object MUST accept or reject this operations when the Job's READ-ONLY "job-state"
454 attribute has the values shown in Table 2. The job's current state MUST affect whether the IPP object
455 accepts or rejects the request. For example, in the case where the operation creates a request for
456 unavailable resources, the Job transitions to a new state. Table 2 shows the allowed behaviors in each
457 job state and the transitions.

458

Table 2 - Job State Transition Table for the Set-Job-Attributes operation

Current "job-state"	New "job-state"	IPP object's response status code and "action":
'pending'	'pending'	'successful-ok'
'pending'	'pending-held'	'successful-ok' - needed resources are not ready
'pending-held'	'pending-held'	'successful-ok'
'pending-held'	'pending'	'successful-ok' - needed resources are ready
'processing'	'processing'	'successful-ok' or 'client-error-not-possible' depending on implementation, including the attributes being set, whether the job has started marking media, etc.
'processing-stopped'	'processing-stopped'	'successful-ok' or 'client-error-not-possible' depending on implementation, including the attributes being set, whether the job has started marking media, etc.
'completed'	'completed'	'client-error-not-possible'
'canceled'	'canceled'	'client-error-not-possible'
'aborted'	'aborted'	'client-error-not-possible'

459

460 This operation MUST NOT change the value of attributes not specified in the operation unless the
 461 definition of the attribute explicitly specifies such side-effects. In general, Job attribute definitions that
 462 are settable will not define side-effects on other attributes that are settable, only side effects on READ-
 463 ONLY attributes, if any.

464 4.2.1 Settable and READ-ONLY Job Description attributes

465 If the Printer supports the "job-message-from-operator" Job Description attribute (see [RFC2911]
 466 section 4.3.16) and the client explicitly supplies a new value for the "job-message-from-operator" in the
 467 Set-Job-Attributes request, then the Printer MUST set the "job-message-from-operator" Job attribute to
 468 this new value.

469 If the Printer supports the Set-Job-Attributes operation, then it SHOULD support setting of:
 470 all Job Template job ("xxx") attributes
 471 that the implementation supports (see [RFC2911] section 4.2 and extensions).

472 Some Job Description attributes (see [RFC2911] section 4.3) MUST NOT be settable, i.e., they are
 473 defined to be READ-ONLY. An attribute marked as "READ-ONLY" in the Job Description attribute
 474 table in Appendix A is such an attribute. The Job attributes not marked as "READ-ONLY" MAY be
 475 settable using the Set-Job-Attributes operation, depending on implementation.

476 Note: From now on, all extensions that define new object attributes will indicate whether or not the
 477 attributes are READ-ONLY, by including the "READ-ONLY" adjective in their descriptions and/or
 478 explicitly stating whether they MAY be settable.

479 *Access Rights:* The authenticated user (see [RFC2911] section 8.3) performing this operation must
480 either be the job owner (as determined in the Job Creation operation) or an operator or administrator of
481 the Printer object (see [RFC2911] Sections 1 and 8.5).

482 **4.2.2 Set-Job-Attributes Request**

483 The following sets of attributes are part of the Set-Job-Attributes Request:

484 Group 1: Operation Attributes

485 Natural Language and Character Set:

486 The "attributes-charset" and "attributes-natural-language" attributes as described in [RFC2911]
487 section 3.1.4.1.

488
489 Target:

490 Either (1) the "printer-uri" (uri) plus "job-id" (integer(1:MAX)) or (2) the "job-uri" (uri)
491 operation attribute(s) which define the target for this operation as described in [RFC2911]
492 section 3.1.5.

493
494 Requesting User Name:

495 The "requesting-user-name" (name(MAX)) attribute SHOULD be supplied by the client as
496 described in [RFC2911] section 8.3.

497 498 Group 2: Job Attributes

499 The client MUST supply a set of Job attributes with one or more values (including explicitly
500 allowed out-of-band values) as defined in [RFC2911] section 4.2 Job Template Attributes
501 ("xxx" attributes), section 4.3 Job Description Attributes, and any attribute extensions
502 supported by the Printer. The value(s) of each Job attribute supplied in Group 2 replaces the
503 value(s) of the corresponding Job attribute on the target Job object. For attributes that can
504 have multiple values (1setOf), all values supplied by the client replace all values of the
505 corresponding Job object attribute.

506
507 If the client supplies an "xxx" attribute with the 'delete-attribute' out-of-band value (see section
508 8.2), the Printer MUST remove the "xxx" attribute from the Job object, if present.

510 **4.2.3 Set-Job-Attributes Response**

511 The IPP object returns the following sets of attributes as part of the Set-Job-Attributes Response:

512 Group 1: Operation Attributes

513 Status Message:

514 In addition to the REQUIRED status code returned in every response, the response
515 OPTIONALLY includes a "status-message" (text(255)) and/or a "detailed-status-message"
516 (text(MAX)) operation attribute as described in [RFC2911] sections 13 and 3.1.6.

517

Natural Language and Character Set:

518

519

The "attributes-charset" and "attributes-natural-language" attributes as described in [RFC2911] section 3.1.4.2.

520

521

522

Group 2: Unsupported Attributes

523

See [RFC2911] section 3.1.7 for details on returning Unsupported Attributes.

524

525

If some of the attributes in the operation fail to validate, the Printer MUST reject the operation, MUST NOT change any Job attributes, and MUST return the indicated status code below. In this group, the Printer MUST also return all attributes that fail to validate. The following are the reasons that an attribute fails to validate and the value returned for the attribute, along with the indicated status code and order of detection:

526

527

528

529

530

531

1. The number of attributes supplied by the client exceeds the maximum number that the Printer supports in a Set-Printer-Attributes request: return the 'client-error-request-entity-too-large' (see [RFC2911] section 13.1.4.9).
2. The Printer doesn't support the attribute: return the attribute with the 'unsupported' out-of-band attribute value (see [RFC2911] section 3.1.7 and [RFC2910]) and the 'client-error-attributes-or-values-not-supported' (see [RFC2911] section 13.1.4.12).
3. The attribute is READ-ONLY (in its definition) or is not-settable in this implementation: return the attribute with the 'not-settable' out-of-band attribute value (see section 8.1) and the 'client-error-attributes-not-settable' status code (see section 7.1).
4. The Printer doesn't support the value: if the attribute in the operation has a single value return it. If the attribute in the operation is multi-valued, return only those values in a 1setOf that are not supported. Return the 'client-error-attributes-or-values-not-supported' status code (see [RFC2911] section 13.1.4.12).
5. The values of some of the supplied attributes conflict with one another and/or other Job attribute values not being set: if the conflicting attribute in the operation has a single value return the attribute and the value. If the attribute in the operation is multi-valued, return only the attribute and those values in a 1setOf that are conflicting with other attributes. Return the 'client-error-conflicting-attributes' status code (see [RFC2911] section 13.1.4.15).

532

533

534

535

536

537

538

539

540

541

542

543

544

545

546

547

548

549

550

4.3 Get-Printer-Supported-Values Operation

551

This OPTIONAL operation allows a client to request the values that the Printer allows in the Set-Printer-Attributes operation for "xxx-supported" attributes. If the Printer supports the Set-Printer-Attributes operation AND some of its "xxx-supported" Printer attributes are settable, then the Printer MUST also support this operation.

552

553

554

555 The Printer MUST return in the Get-Printer-Supported-Values response those, and only those, "xxx-
556 supported" Printer attributes that it supports setting with the Set-Printer-Attributes operation.
557 Furthermore, if a client requests the value of an attribute that is not settable or is not supported (as in
558 the Get-Printer-Attributes response), the Unsupported Attributes Group of the response NEED NOT
559 contain the "requested-attributes" operation attribute with any such requested (attribute keyword)
560 values.

561 This operation has identical request/response attributes to the Get-Printer-Attributes operation in
562 IPP/1.1 [RFC2911]. The operation also behaves identically to the Get-Printer-Attributes operation in
563 IPP/1.1 [RFC2911] with the following exceptions:

- 564 1. The Get-Printer-Supported-Values operation supports only "xxx-supported" attributes.
- 565 2. The Get-Printer-Attributes operation returns the few "xxx-supported" attributes that are defined to
566 be single valued, such as "page-ranges-supported" (boolean) or "pdl-override-supported" (type2
567 keyword), as single values, while Get-Printer-Supported-Values returns the possible values that can
568 be set as a lsetOf of the same attribute syntax type (See Appendix B: Attributes returned from Get-
569 Printer-Supported-Values).
- 570 3. The Get-Printer-Attributes operation returns the current values of requested attributes while the
571 Get-Printer-Supported-Values operation returns the values that are inherently supported by the
572 implementation code, i.e., the values that an administrative client can set in a Set-Printer-Attributes
573 request.
- 574 4. The Get-Printer-Attributes operation returns the current values of requested "xxx-supported"
575 attributes that the Printer is configured to accept in Job Creation operations, including additional
576 values defined by the administrator, while the Get-Printer-Supported-Values operation returns only
577 the values of "xxx-supported" attributes that are inherently supported by the implementation and
578 does not return any additional values defined by the administrator where the implementation
579 supports the 'admin-define' out-of-band value.
- 580 5. The Get-Printer-Attributes never returns the 'admin-define' out-of-band attribute value, while the
581 Get-Printer-Supported-Attributes operation does, if the implementation allows the administrator to
582 define name values by setting that "xxx-supported" attribute with any 'name' value(s).
- 583 6. The Get-Printer-Attributes operation only requires end-user access rights, while the Get-Printer-
584 Supported-Values requires administrator access rights.

585 *Access Rights:* The authenticated user (see [RFC2911] section 8.3) performing this operation must be
586 an administrator of the Printer object (see [RFC2911] Sections 1 and 8.5).

587 **4.3.1 Definition of the usage of the 'admin-define' out-of-band attribute value**

588 If the Set-Printer-Attributes operation allows the System Administrator to define arbitrary 'name' values
589 for an "xxx-supported" attribute, then the Get-Printer-Supported-Values operation MUST return the
590 'admin-define' out-of-band attribute value (see section 8.3) as one of the values of the "xxx-supported"

591 attribute. In other words, the 'admin-define' out-of-band attribute value indicates that the Printer
592 implementation supports clients setting arbitrary 'name' attribute syntax values for that "xxx-supported"
593 attribute using the Set-Printer-Attributes operation as long as the attribute is defined with the 'name'
594 attribute syntax.

595 For example, if the Get-Printer-Supported-Values operation returns several keywords as the value of
596 the "media-supported" attribute, then the Set-Printer-Attributes operation MUST accept any of these
597 keywords as values for the "media-supported" attribute. If the Get-Printer-Supported-Values operation
598 returns an 'admin-define' out-of-band attribute value as one of the values of the "media-supported"
599 attribute, then the Set-Printer-Attributes operation MUST accept any value whose attribute syntax is
600 'name' as a value for the "media-supported" attribute (provided that the user is properly authenticated to
601 use the Set-Printer-Attributes operation, e.g., has administrative access rights).

602 The Get-Printer-Supported-Values MAY return the 'admin-define' out-of-band attribute value for any
603 IPP/1.1 or extension Job Template attribute if the implementation supports allowing the System
604 Administrator to add values to the "xxx-supported" attribute using the Set-Printer-Attributes operation.
605 In this case, the Printer MUST accept any 'name' value of the correct attribute syntax in a Set-Printer-
606 Attributes operation that is setting that attribute. For "xxx-supported" attributes that are defined with a
607 choice of attribute syntaxes, such as 'keyword | name', it is the 'name' attribute syntax that the System
608 Administrator can use to add new values, not the 'keyword' attribute syntax. For IPP/1.1 this
609 requirement includes the following Job Template attributes:

610 media-supported
611 job-hold-until-supported
612 job-sheets-supported

613
614 Implementations that support additional Job Template attributes that include the 'name' attribute syntax,
615 MAY use the 'admin-define' out-of-band value with them.

616 If the 'admin-define' out-of-band attribute value is not one of the values of an "xxx-supported" attribute
617 returned in a Get-Printer-Supported-Values response, then the Printer MUST NOT allow the Set-
618 Printer-Attributes operation for that attribute to contain a value that is not one of the explicit 'keyword'
619 or 'name' values returned in a Get-Printer-Supported-Values response.

620 See Appendix B: Attributes returned from Get-Printer-Supported-Values for a full list of values
621 returned by this operation.

622 **5 New Operation attributes**

623 This section defines new operation attributes for use with the IPP/1.1 operations indicated. As new
624 operations are defined they will also indicate explicitly whether these operation attributes are defined for
625 use with them.

5.1 printer-message-from-operator (text(127))

The Printer SHOULD support this Operation attribute in following operations if it supports the corresponding "printer-message-from-operator" Printer Description attribute.

Pause-Printer
Resume-Printer
Purge-Jobs

The client OPTIONALLY supplies this attribute in the above operations. The value of this attribute is a message from the operator about the Printer object on which the operator is performing the operation. If this operation attribute is supported, the Printer copies the value to its "printer-message-from-operator" Printer Description attribute (see [RFC2911] section 4.4.25) even if this Operation attribute is a zero-length text value or consists solely of white space.

If the Printer supports this operation attribute, it MUST support both a zero-length text value and the 'no-value' out-of-band value (see [RFC2911] section 4.1) to indicate that the operator has sent no message. In this case, the Printer sets the value of the "printer-message-from-operator" to the zero-length value or 'no-value' out-of-band value, respectively. If the client queries the "printer-message-from-operator" Printer attribute, the Printer returns the attribute with the zero-length value or the 'no-value' value, respectively.

In addition, the Printer automatically copies:

1. the value of its "printer-up-time" attribute (see [RFC2911] section 4.4.29) to its "printer-message-time" attribute,
2. the value of its "printer-current-time" (dateTime) attribute (see [RFC2911] section 4.4.30) to its "printer-message-date-time" attribute, if supported.

If the client omits this operation attribute, the Printer does not change the value of its "printer-message-from-operator", "printer-message-time" and "printer-message-date-time" Printer Description attributes.

The "printer-message-from-operator" operation attribute MUST NOT be supported as an operation attribute for the Set-Printer-Attributes operation. If the operator wants to set the Printer's "printer-message-from-operator" Printer Description attribute when issuing the Set-Printer-Attributes operation, the client supplies the "printer-message-from-operator" explicitly with its new value as one of the Printer Description attributes in Group 2 in the request. The Printer also updates its "printer-message-time" and "printer-message-date-time" Printer Description attributes. If the client does not explicitly supply the "printer-message-from-operator" with its new value in the Set-Printer-Attributes request, the Printer leaves the value of the Printer's "printer-message-from-operator" Printer Description attribute unchanged.

660 5.2 job-message-from-operator (text(127))

661 The Printer SHOULD support this Operation attribute in following operations if it supports the
662 corresponding "job-message-from-operator" Job Description attribute.

663 Cancel-Job
664 Hold-Job
665 Release-Job
666 Restart-Job

667
668 The client OPTIONALLY supplies this attribute in the above operations. The value of this attribute is a
669 message from the operator about the Job object on which the operator has just performed an operation.
670 If supported, the Printer copies the value to the Job's "job-message-from-operator" Job Description
671 attribute (see [RFC2911] section 4.3.16) (even if this Operation attribute is a zero-length text value or
672 consists solely of white space).

673 If the Printer supports this operation attribute, it MUST support both a zero-length text value and the
674 'no-value' out-of-band value (see [RFC2911] section 4.1) to indicate that the operator has sent no
675 message. In this case, the Printer sets the value of the "job-message-from-operator" to the zero-length
676 value or 'no-value' out-of-band value, respectively. If the client queries the "job-message-from-
677 operator" Job attribute, the IPP object returns the attribute with the zero-length value or the 'no-value'
678 value, respectively.

679 If the client omits this attribute, the Printer does not change the value of its "job-message-from-
680 operator" Job Description attribute.

681 Note: There are no corresponding 'job-message-time" and "job-message-date-time" Job Description
682 attributes, since the usual lifetime of a job is limited.

683 The "job-message-from-operator" operation attribute MUST NOT be supported as an operation
684 attribute for the Set-Job-Attributes operation. If the operator wants to set the Job's "job-message-from-
685 operator" Job Description attribute when issuing the Set-Job-Attributes operation, the client MUST
686 supply the "job-message-from-operator" with its new value as one of the Job Description attributes in
687 Group 2 in the request. Otherwise, the Printer leaves the value of the Job's "job-message-from-
688 operator" Job Description attribute unchanged by not explicitly setting the attribute. If the client does
689 not explicitly supply the "job-message-from-operator" with its new value in the Set-Job-Attributes
690 request, the Printer leaves the value of the Job's "job-message-from-operator" Job Description attribute
691 unchanged.

692 6 New Printer Description Attributes

693 The following new Printer Description attributes are needed to support the new operations defined in
694 this document.

6.1 printer-settable-attributes-supported (1setOf type2 keyword)

This REQUIRED READ-ONLY Printer attribute identifies the Printer object attributes that are settable in this implementation, i.e., that are settable using the Set-Printer-Attributes operations (see section 4.1). This attribute MUST be supported if the Set-Printer-Attributes operations is supported. The Printer MUST reject attempts to set any Printer attributes that are not one of the values of this attribute, returning the 'client-error-attributes-not-settable' status code (see section 7.1). The value of this attribute MAY depend on the value of the "document-format" operation attribute supplied in the Get-Printer-Attributes operation (see [RFC2911] section 3.2.5.1).

Standard keyword values are:

'none': There are no settable Printer attributes.

'xxx': Where 'xxx' is any of the keyword attribute names allowed by section 4.1.1

6.2 job-settable-attributes-supported (1setOf type2 keyword)

This REQUIRED READ-ONLY Printer attribute identifies the Job object attributes that are settable in this implementation, i.e., that are settable using the Set-Job-Attributes operation (see section 4.2). This attribute MUST be supported if the Set-Job-Attributes operations is supported. The Printer MUST reject attempts to set any Job attributes that are not one of the values of this attribute, returning the 'client-error-attributes-not-settable' status code (see section 7.1).

Standard keyword values are:

'none': There are no settable Job attributes.

'xxx': Where 'xxx' is any of the keyword attribute names allowed by section 4.2.1.

6.3 document-format-varying-attributes (1setOf type2 keyword)

This OPTIONAL READ-ONLY Printer Description attribute contains a set of attribute name keywords. This attribute SHOULD be supported by a Printer object, if the Printer object has Printer attributes whose value vary depending on document format (see [RFC2911] Get-Printer-Attributes operation). This attribute specifies which attribute values can vary by document-format. If an attribute's name "xxx" is a member of this attribute and the value of attribute "xxx" is changed with the Set-Printer-Attributes operation that included the "document-format" operation attribute, then the Printer MUST change the value for the specified document format and no other document formats (see section 4.1.2). If an attribute's name "xxx" is not a member of this attribute and the value of attribute "xxx" is changed with the Set-Printer-Attributes operation, then the attribute is changed for all document formats (whether or not the client supplied the "document-format" operation attribute).

6.4 printer-message-time (integer(MIN:MAX))

This OPTIONAL READ-ONLY Printer Description attribute contains the time that the Printer's "printer-message-from-operator" was changed by the operator using any operation where the client supplied the "printer-message-from-operator" operation attribute (see section 5.1) or was explicitly set

730 using the Set-Printer-Attributes operation (see section 4.1). This attribute allows the users to know
731 when the "printer-message-from-operator" attribute was last set.

732 The Printer sets the value of this attribute by copying the value of the Printer's "printer-up-time"
733 attribute (see [RFC2911] section 4.3.14). If the Printer resets its "printer-up-time" attribute to 1 on
734 power-up, then it MUST change the value of the "printer-message-time" to 0 or a negative number as
735 specified in [RFC2911] section 4.3.14.

736 Note: This attribute helps users better understand the context for the "printer-message-from-operator"
737 message.

738 **6.5 printer-message-date-time (dateTime)**

739 This OPTIONAL READ-ONLY Printer Description attribute contains the date and time that the
740 Printer's "printer-message-from-operator" was changed by the operator using any operation where the
741 client supplied the "printer-message-from-operator" operation attribute (see section 5.1) or was
742 explicitly set using the Set-Printer-Attributes operation (see section 4.1). This attribute allows the users
743 to know when the "printer-message-from-operator" attribute was last set.

744 This attribute MUST be supported if the Printer supports both the "printer-message-time" and the
745 "printer-current-time" (dateTime) attributes (see [RFC2911] section 4.4.30).

746 Note: This attribute helps users better understand the context for the "printer-message-from-operator"
747 message.

748 **6.6 printer-xri-supported (1setOf collection)**

749 This OPTIONAL Printer Description attribute is a multi-valued attribute where each value has the
750 'collection' attribute syntax (see [ipp-coll]) containing member attributes with the same semantics as the
751 following IPP/1.1 READ-ONLY Printer Description attributes, except for cardinality:

752 printer-uri-supported (1setOf uri) - see [RFC2911] section 4.4.1
753 uri-authentication-supported (1setOf type2 keyword) - see [RFC2911] section 4.4.2
754 uri-security-supported (1setOf type2 keyword) - see [RFC2911] section 4.4.3
755

756 When setting the "printer-xri-supported" attribute with a Set-Printer-Attributes request, the Printer
757 MUST also set these three IPP/1.1 READ-ONLY Printer Description attributes as a defined side effect.
758 Thus, this collection attribute provides the means to set these three IPP/1.1 READ-ONLY attributes
759 atomically so that they are never left in a partially inconsistent state.

760 An IPP Printer MUST NOT provide any other way using IPP to set these three IPP/1.1 READ-ONLY
761 Printer Description attributes, since they are READ-ONLY and MUST have consistent values at all
762 times. Note: The "xri-printer-supported" (1setOf collection) attribute can be put into a directory
763 schema that requires a single text string value, such as SLP or LDAPA, by using suitable delimiting

764 characters to separate member attributes of the collection and/or terminating collection values. See
765 [svrloc-printer] and [ldap-printer].

766 The member attributes of the "printer-xri-supported" (1setOf collection) are given in Table 3.

767 **Table 3 - Member attributes of "printer-xri-supported" (1setOf collection)**

Member attribute	client MUST supply	Printer MUST support
xri-uri (uri)	yes	yes
xri-authentication (1setOf type2 keyword)	yes	yes
xri-security (1setOf type2 keyword)	yes	yes

768 Each collection value MUST contain a single unique value for the "xri-uri" member attribute. However,
769 the other two member attributes are multi-valued, so that a single URI can support more than one
770 authentication scheme and/or more than one security scheme. Other than the uniqueness and the
771 cardinality requirements, the semantics of these three member attributes is given in [RFC2911] sections
772 4.4.1, 4.4.2, and 4.4.3, respectively.
773

774 A client can query the current values using the Get-Printer-Attributes operation by supplying either:

- 775 1. the three IPP/1.1 attribute names: "printer-uri-supported", "uri-authentication-supported", "uri-
776 security-supported" and getting back the parallel values OR
- 777 2. the single attribute name: "printer-xri-supported" and getting back the 1setOf collection which
778 contains the same information semantically, but in a different form.

779 A client can query what member attribute values can be set by supplying the three attribute names: "xri-
780 uri-scheme-supported", "xri-authentication-supported", and "xri-security-supported" in a Get-Printer-
781 Supported-Values request and getting back the uriScheme and type2 keyword values that can be set.
782 Since the "printer-xri-supported", "uri-authentication-supported", and "uri-security-supported"
783 attributes are READ-ONLY, they are not queriable with the Get-Printer-Supported-Values operation
784 (see section 4.3). See Table 16.

785 When performing a Set-Printer-Attributes operation, if there are multiple values for the "xri-
786 authentication" and/or "xri-security" member attributes, the Printer MUST set the corresponding three
787 READ-ONLY attributes with all possible combinations of values. For example, setting the "printer-xri-
788 supported" with the following two collection values where the first URI has both 'basic' and 'digest'
789 authentication:

```
790     "printer-xri-supported" =
791     {   "xri-uri" = ipp://abc.com/p1
792         "xri-authentication" = basic, digest
793         "xri-security" = tls
794     },
795     {   "xri-uri" = http://abc.com/pq
796         "xri-authentication" = none
797         "xri-security" = none
798     }
799
```

would cause the Printer to set the three corresponding IPP/1.1 READ-ONLY attributes, each with three parallel values as follows:

```
802     "printer-uri-supported" = { ipp://abc.com/p1, ipp://abc.com/p1,
803                               http://abc.com/pq }
804     "uri-authentication-supported" = { basic, digest, none }
805     "uri-security-supported" = { tls, tls, none }
806
```

Because there were two authentication values for the `ipp://abc.com/p1` URL, that URL value is repeated. Had the `ipp` URL had 2 authentication values and 3 security values, then there would have been 7 ($2*3 + 1$) parallel values for each of the three attributes, 6 with the same `ipp` URI and 1 with the `http` URI.

811 6.7 xri-uri-scheme-supported (1setOf uriScheme)

This OPTIONAL READ-ONLY Printer Description attribute identifies the URI schemes that the implementation supports for use in the "printer-uri-supported" (1setOf uri) Printer Description attribute (see [RFC2911] section 4.4.1) and the "xri-uri" member attribute of the "xri-printer-supported" (1setOf collection) Printer Description attribute (see section 6.6).

A Printer MUST support this attribute if it supports setting the "printer-xri-supported" (1setOf collection) with the Set-Printer-Attributes operation.

818 6.8 xri-authentication-supported (1setOf type2 keyword)

This OPTIONAL READ-ONLY Printer Description attribute identifies the Client Authentication mechanisms that the implementation supports for use in the "uri-authentication-supported" (1setOf type2 keyword) Printer Description attribute (see [RFC2911] section 4.4.2) and the "xri-authentication" member attribute of the "xri-printer-supported" (1setOf collection) Printer Description attribute (see section 6.6).

A Printer MUST support this attribute if it supports setting the "printer-xri-supported" (1setOf collection) with the Set-Printer-Attributes operation.

826 **6.9 xri-security-supported (1setOf type2 keyword)**

827 This OPTIONAL READ-ONLY Printer Description attribute identifies the URI schemes that the
828 implementation supports for use in the "uri-security-supported" (1setOf type2 keyword) Printer
829 Description attribute (see [RFC2911] section 4.4.3) and the "xri-security" member attribute of the "xri-
830 printer-supported" (1setOf collection) Printer Description attribute (see section 6.6).

831 A Printer MUST support this attribute if it supports setting the "printer-xri-supported" (1setOf
832 collection) with the Set-Printer-Attributes operation.

833 **7 Additional status codes**

834 This section defines new status codes used by the operations defined in this document.

835 **7.1 client-error-attributes-not-settable (0x0413)**

836 The Set-Printer-Attributes or Set-Job-Attributes operation failed because one or more of the specified
837 attributes cannot be set either because the attribute is defined to be READ-ONLY or the attribute is not
838 settable in this implementation (see sections 4.1.3 and 4.2.3), the Printer MUST return this error code
839 and the attribute keyword name(s) and the 'not-settable' out-of-band value (see section 8.1) in the
840 Unsupported Attributes Group(see [RFC2911] section 3.1.7) for all of the attributes that could not be
841 set. When the Printer returns this status, it MUST NOT change any of the attributes supplied in the
842 operation.

843 **8 Additional out-of-band values**

844 This section defines additional out-of-band values. As with all out-of-band values, a client or a Printer
845 MUST NOT use an out-of-band value unless the definition of the attribute in an operation request
846 and/or response explicitly allows such usage. See the beginning of [RFC2911] section 4.1.

847 **8.1 'not-settable' out-of-band value**

848 The 'not-settable' out-of-band attribute value is returned by the IPP Printer in the Unsupported
849 Attributes group of a response to indicate that the attribute supplied by the client in the request is
850 READ-ONLY by definition or is not settable in this implementation.

851 The 'not-settable' out-of-band attribute value is defined for use with the Set-Job-Attributes and Set-
852 Printer-Attributes response only. If a future additional "set" operation allows the 'not-settable' out-of-
853 band value, its definition document MUST indicate such use explicitly, including with which attributes.

854 An IPP object MUST support the 'not-settable' out-of-band value in a Set-Job-Attributes or Set-Printer-
855 Attributes request if it supports those operations. A client MUST NOT supply the 'not-settable' out-of-

856 band value in any request. An IPP object MUST NOT support the 'not-settable' out-of-band value in
857 other operations, unless the operations' definition document explicitly defines such usage. If a Printer
858 receives this out-of-band value in any operation request, the Printer MUST either (1) reject the entire
859 request and return the 'client-error-bad-request' status code or (2) ignore the attribute and return it with
860 the 'unsupported' out-of-band value.

861 See sections 4.1.3 and 4.2.3 in this document for an example definition of the usage of the 'not-settable'
862 out-of-band value in the Set-Printer-Attributes and Set-Job-Attributes responses.

863 **8.1.1 Encoding of the 'not-settable' out-of-band attribute value**

864 The encoding of the 'not-settable' out-of-band value is 0x15 (see [RFC2910]). The value-length MUST
865 be 0 and the value empty.

866 **8.2 'delete-attribute' out-of-band value**

867 The 'delete-attribute' out-of-band attribute value is supplied by the client in a request to indicate that the
868 Printer is to remove the supplied attribute and all of its values from the target object, if present.

869 The 'delete-attribute' out-of-band attribute value is defined for use with the Set-Job-Attributes request
870 only. If a future additional "set" operation allows the 'delete-attribute' out-of-band value, its definition
871 document MUST indicate such use explicitly, including with which attributes.

872 An IPP Printer MUST support the 'delete-attribute' out-of-band value if it supports the Set-Job-
873 Attributes operation. A client MUST NOT supply and an IPP object MUST NOT support the 'delete-
874 attribute' out-of-band value in other operations, unless the operations' definition document explicitly
875 defines such usage. For example, the 'delete-attribute' out-of-band value MUST NOT be used in the
876 Set-Printer-Attributes operation, where the absence of an attribute from an IPP object indicates that the
877 attribute is not supported. If a Printer receives this out-of-band value in other operation requests, the
878 Printer MUST either (1) reject the entire request and return the 'client-error-bad-request' status code or
879 (2) ignore the attribute and return it with the 'unsupported' out-of-band value.

880 See section 4.2 in this document for the definition of the usage of the 'delete-attribute' out-of-band value
881 in the Set-Job-Attributes request.

882 **8.2.1 Encoding of the 'delete-attribute' out-of-band value**

883 The encoding of the 'delete-attribute' out-of-band value is 0x16 (see [RFC2910]). The value-length
884 MUST be 0 and the value empty.

885 **8.3 'admin-define' out-of-band attribute value**

886 Section 4.3 defines the Get-Printer-Supported-Values response to contain the values of an "xxx-
887 supported" attribute that are supported by the implementation before any additional value are defined by
888 the administrator. The 'admin-define' out-of-band attribute value is returned as an additional value of an

889 "xxx-supported" attribute in a Get-Printer-Supported-Values response to indicate that the
890 implementation supports allowing an administrator to define additional arbitrary 'name' values for that
891 "xxx-supported" attribute.

892 For example, if the "media-supported" (1setOf (type3 keyword | name)) attribute contains this value,
893 then the Printer MUST permit an administrator to add new media names to the Printer's "media-
894 supported" attribute. In order for an administrator to add new values to a Printer's "xxx-supported"
895 attribute, the client supplies the existing and new values in a Set-Printer-Attributes request for that
896 attribute. The client MUST supply any such administratively defined values in the Set-Printer-
897 Attributes request using the 'name' attribute syntax.

898 The 'admin-define' out-of-band attribute value is defined for use with the Get-Printer-Supported-Values
899 response only. A Printer MUST NOT return the 'admin-define' out-of-band value in a Get-Printer-
900 Attributes response, since such a response indicates what an end-user client can supply in a Job Creation
901 operation. If a future additional "get" operation allows the 'admin-define' out-of-band value, its
902 definition document MUST indicate such use explicitly, including with which attributes.

903 An IPP Printer MUST support the 'admin-define' out-of-band value, if it supports a client setting
904 arbitrary 'name' values of an "xxx-supported" Printer attribute using the Set-Printer-Attributes
905 operation. A client MUST NOT supply the 'admin-define' out-of-band value in any request. An IPP
906 object MUST NOT support the 'admin-define' out-of-band value in other operations, unless the
907 operations' definition document explicitly defines such usage. If a Printer receives this out-of-band
908 value in any operation request, the Printer MUST either (1) reject the entire request and return the
909 'client-error-bad-request' status code or (2) ignore the attribute and return it with the 'unsupported' out-
910 of-band value.

911 This document defines that the 'admin-define' out-of-band value MUST be used only with "xxx-
912 supported" attributes that are defined to include the 'name' attribute syntax. This out-of-band value is
913 not intended to be used with "xxx-supported" attributes of other attribute syntaxes, such as 'uri', even
914 though the administrator defines arbitrary values for such attributes. If other documents extend the use
915 of the 'admin-define' out-of-band value to other attribute syntaxes, such a document MUST define such
916 use explicitly, including with which attributes.

917 See section 4.3 in this document for an example definition of the usage of the 'admin-define' out-of-band
918 attribute value in any "xxx-supported" attribute returned in a Get-Printer-Supported-Values response
919 that is defined to include the 'name' attribute syntax.

920 **8.3.1 Encoding of the 'admin-define' out-of-band attribute value**

921 The encoding of the 'admin-define' out-of-band attribute value is 0x17 (see [RFC2910]). The value-
922 length MUST be 0 and the value empty.

923 **9 New Values for Existing Printer Description Attributes**

924 This section contains those attributes for which additional values are added.

925 **9.1 operations-supported (1setOf type2 enum)**

926 The following "operation-id" values are added in order to support the new operations defined in this
 927 document:

928 **Table 4 – Operation-id assignments**

<u>Value</u>	<u>Operation Name</u>
<u>0x0013</u>	<u>Set-Printer-Attributes</u>
<u>0x0014</u>	<u>Set-Job-Attributes</u>
<u>0x0015</u>	<u>Get-Printer-Supported-Values</u>

929 **10 Conformance Requirements**

930 This section specifies the conformance requirements for clients and IPP objects.

931 Both the Set-Job-Attributes and the Set-Printer-Attributes operations defined in the document are
 932 OPTIONAL for an IPP object to support. Either one MAY be supported without the other or both
 933 MAY be supported. However, if the Set-Printer-Attributes operation is supported, then the Get-
 934 Printer-Supported-Values operation MUST be supported if any "xxx-supported" attributes are settable.
 935 Otherwise, the Get-Printer-Supported-Values operation is OPTIONAL for an IPP Printer to support.

936 If the Set-Printer-Attributes operation is supported, then the Printer MUST support the following
 937 additional items:

- 938 1. the Get-Printer-Supported-Values operation (see section 5), if any "xxx-supported" attributes
 939 are settable.
- 940 2. the "printer-settable-attributes-supported" Printer Description attribute (see section 6.1)
- 941 3. the 'not-settable' out-of-band value in responses (see section 8.1)
- 942 4. the 'client-error-not-settable' status code (see section 7.1)
- 943 5. If "printer-message-from-operator" Printer Description attribute is supported (see [RFC2911]
 944 section 4.4.25), then it MUST be settable.
- 945 6. the Get-Printer-Supported-Values operation (see section 4.3), if any "xxx-supported" attributes
 946 are settable.

- 947 7. If a client can set a value with the 'name' attribute syntax for one or more "xxx-supported"
948 attributes, then the 'admin-define' out-of-band attribute value (see section 8.3) MUST be
949 supported in the Get-Printer-Supported-Values response for each such settable attribute (see
950 section 4.3)

951 If the Set-Job-Attributes operation is supported, then the Printer MUST support the following
952 additional items:

- 953 1. the "job-settable-attributes-supported-" Printer Description attribute (see section 6.2)
954 2. the 'not-settable' out-of-band value in responses (see section 8.1)
955 3. the 'delete-attribute' out-of-band value in requests (see section 8.2)
956 4. the 'client-error-not-settable' status code (see section 7.1)
957 5. If the "job-message-from-operator" Printer Description attribute is supported (see [RFC2911]
958 4.3.16), then it MUST be settable.

959 It is OPTIONAL for the Printer object to support the "printer-message-time" (integer) and "printer-
960 message-date-time" (dateTime) Printer Description attributes. If both the "printer-message-time"
961 (integer) and the "printer-current-time" (dateTime) (see [RFC2911] section 4.4.30) attributes are
962 supported, then the "printer-message-date-time" (dateTime) Printer Description attribute MUST be
963 supported.

964 As with all out-of-band values, a client or a Printer MUST NOT use an out-of-band value unless the
965 definition document for the attribute in an operation request and/or response explicitly allows such
966 usage.

967 11 IANA Considerations

968 This section contains ~~the exact~~[registration](#) information for IANA to add to the [various](#) IPP Registries
969 according to the procedures defined in RFC 2911 [RFC2911] section 6.

970 *Note to RFC Editors: Replace RFC NNNN below with the RFC number for this document, so that it*
971 *accurately reflects the content of the information for the IANA Registry.*
972

973 11.1 Operation Registrations

974 The [following table lists all of the](#) operations defined in this document. ~~It will be published by IANA~~
975 [These are to be registered](#) according to the procedures [defined](#) in RFC 2911 [RFC2911] section 6.4.
976 [with the following path:](#)

977 <ftp://isi.edu/iana/assignments/ipp/operations/>
978
979

980 ~~The registry entry will contain the following information:~~

981	Operations:	Ref.	Section:
982	Set-Printer-Attributes	RFC NNNN	4.1
983	Set-Job-Attributes	RFC NNNN	4.2
984	Get-Printer-Supported-Values	RFC NNNN	4.3
985			

986
987 ~~The resulting operation registrations will be published in the~~
988 ~~<ftp://ftp.iana.org/in-notes/iana/assignments/ipp/operations/>~~
989 ~~area.~~

990 **11.2 Additional Enum Attribute Value Registrations for the “operations-supported” Printer** 991 **Attribute**

992 ~~The following table lists all the new enum attribute values defined in this document as additional type2~~
993 ~~enum values for use with the “operations-supported” Printer Description attribute. These are to be~~
994 ~~registered according to the procedures defined in RFC 2911 [RFC 2911] section 6.1.~~

995	Enum Attribute Values:	Value	Ref.	Section:
996	Set-Printer-Attributes	0x0013	RFC NNNN	4
997	Set-Job-Attributes	0x0014	RFC NNNN	4
998	Get-Printer-Supported-Values	0x0015	RFC NNNN	4
999				

000
001 ~~The resulting enum attribute value registrations will be published in the~~
002 ~~<ftp://ftp.iana.org/in-notes/iana/assignments/ipp/attribute-values/operations-supported/>~~
003 ~~area.~~

004 **11.3 Attribute Registrations**

005 The ~~following table lists all of the~~ attributes defined in this document. ~~will be published by IANA. These~~
006 ~~are to be registered~~ according to the procedures in RFC 2911 [RFC2911] section 6.2. ~~with the~~
007 ~~following path:~~

008
009 ~~<ftp://ftp.isi.edu/iana/assignments/ipp/attributes/>~~

010
011 ~~The registry entry will contain the following information:~~

012	Operation attributes:	Ref.	Section:
013	printer-message-from-operator (text(127))	RFC NNNN	5.1
014	job-message-from-operator (text(127))	RFC NNNN	5.2
015			

016

		Ref.	Section:
017	Printer Description attributes:		
018	printer-settable-attributes-supported (1setOf type2 keyword)		
019		RFC NNNN	6.1
020	job-settable-attributes-supported (1setOf type2 keyword)		
021		RFC NNNN	6.2
022	document-format-varying-attributes (1setOf type2 keyword)		
023		RFC NNNN	6.3
024	printer-message-time (integer(MIN:MAX))	RFC NNNN	6.4
025	printer-message-date-time (dateTime)	RFC NNNN	6.5
026	printer-xri-supported (1setOf collection)	RFC NNNN	6.6
027	xri-uri-scheme-supported (1setOf uriScheme)	RFC NNNN	6.7
028	xri-authentication-supported (1setOf type2 keyword)		6.8
029	xri-security-supported (1setOf type2 keyword)	RFC NNNN	6.9

031 The resulting attribute registrations will be published in the
 032 <ftp://ftp.iana.org/in-notes/iana/assignments/ipp/attributes/>
 033 [area.](#)
 034

035 11.4 Status code Registrations

036 The following table lists the status codes defined in this document. will be published by IANA. This is to
 037 be registered according to the procedures in RFC 2911 [RFC2911] section 6.6. with the following path:

038 [ftp.isi.edu/iana/assignments/ipp/status-codes/](ftp://ftp.isi.edu/iana/assignments/ipp/status-codes/)

041 The registry entry will contain the following information:

		Ref.	Section:
043	Status codes:		
044	client-error-attributes-not-settable (0x0413)	RFC NNNN	7.1

046 The resulting status code registration will be published in the
 047 <ftp://ftp.iana.org/in-notes/iana/assignments/ipp/status-codes/>
 048 [area.](#)
 049

050 11.5 Out-of-band Attribute Value Registrations

051 The following table lists all of the out-of-band attribute values defined in this document. will be
 052 published by IANA. These are to be registered according to the procedures in RFC 2911 [RFC2911]
 053 section 6.7. with the following path:

054 [ftp.isi.edu/iana/assignments/ipp/out-of-band-attribute-value-tags/](ftp://ftp.isi.edu/iana/assignments/ipp/out-of-band-attribute-value-tags/)

057 The registry entry will contain the following information:
 058

	Out-of-band Attribute Values:	Ref.	Section:
059	'not-settable' out-of-band value	RFC NNNN	8.1
060	'delete-attribute' out-of-band value	RFC NNNN	8.2
061	'admin-define' out-of-band attribute value	RFC NNNN	8.3
062			
063			

064 [The resulting out-of-band attribute value registrations will be published in the](http://ftp.iana.org/in-notes/iana/assignments/ipp/out-of-band-attribute-value-tags/)
065 ftp.iana.org/in-notes/iana/assignments/ipp/out-of-band-attribute-value-tags/
066 [area.](http://ftp.iana.org/in-notes/iana/assignments/ipp/out-of-band-attribute-value-tags/)

067 12 Internationalization Considerations

068 This document has the same localization considerations as the [RFC2911].

069 13 Security Considerations

070 The IPP Model and Semantics document [RFC2911 section 8] discusses high level security
071 requirements (Client Authentication, Server Authentication and Operation Privacy). Client
072 Authentication is the mechanism by which the client proves its identity to the server in a secure manner.
073 Server Authentication is the mechanism by which the server proves its identity to the client in a secure
074 manner. Operation Privacy is defined as a mechanism for protecting operations from eavesdropping.

075 In addition, the introduction of the Set-Printer-Attributes and Set-Job-Attributes operations creates
076 another security threat, since the client is able to modify the Printer and Job attributes stored in the
077 Printer. Such modifications could lead to denial of service.

078 A malicious user could alter the policy established by the system administrator and stored in the Printer
079 attributes. Such alteration could either grant access to more resources or deny access to resources that
080 the system administrator has established. For example, the malicious user could remove all of the
081 document-format values from the "document-format-supported" Printer attribute so that the Printer
082 would refuse to accept all jobs.

083 The general remedy for such malicious user actions against Printer attributes is to have strong Client
084 Authentication coupled with Printer access control to limit the users who have System Administrator or
085 Operator privileges.

086 A malicious user could modify the Job Template attributes of another user's Job, such as the "copies"
087 attribute. For example, setting the number of copies to a large number.

088 The general remedy for such malicious user actions against another user's job is to have strong Client
089 Authentication coupled with Printer access control to limit the users who have System Administrator or
090 Operator privileges who can modify any job and, in addition, store the Client Authentication with each
091 Job so that only the job owner End User can modify his/her own job.

092 **14 Author's Addresses**

093 Carl Kugler
094 IBM
095 P.O. Box 1900
096 Boulder, CO 80301-9191

097
098 Phone: (303) 924-5060
099 FAX:
100 e-mail: kugler@us.ibm.com

101
102 Tom Hastings
103 Xerox Corporation
104 737 Hawaii St. ESAE 231
105 El Segundo, CA 90245

106
107 Phone: 310-333-6413
108 Fax: 310-333-5514
109 e-mail: hastings@cp10.es.xerox.com

110
111 Robert Herriot
112 Xerox Corp.
113 3400 Hill View Ave, Building 1
114 Palo Alto, CA 94304

115
116 Phone: 650-813-7696
117 Fax: 650-813-6860
118 e-mail: robert.herriot@pahv.xerox.com

119
120 Harry Lewis
121 IBM
122 P.O. Box 1900
123 Boulder, CO 80301-9191

124
125 Phone: (303) 924-5337
126 FAX:
127 e-mail: harryl@us.ibm.com

128
129 IPP Web Page: <http://www.pwg.org/ipp/>
130 IPP Mailing List: ipp@pwg.org

131
132 To subscribe to the ipp mailing list, send the following email:
133 1) send it to majordomo@pwg.org
134 2) leave the subject line blank
135 3) put the following two lines in the message body:

136 [subscribe ipp](#)
137 [end](#)

138
139 [Implementers of this specification document are encouraged to join the IPP Mailing List in order to](#)
140 [participate in any discussions of clarification issues and review of registration proposals for additional](#)
141 [attributes and values. In order to reduce spam the mailing list rejects mail from non-subscribers, so you](#)
142 [must subscribe to the mailing list in order to send a question or comment to the mailing list.](#)

143 15 References

144 [ipp-coll]

145 deBry, R., , Hastings, T., Herriot, R., "Internet Printing Protocol (IPP): The Collection Attribute
146 Syntax", <draft-ietf-ipp-collection-052.txt doc>, work in progress, [March 9, 2000](#)[July 17, 2001](#).

147 [ipp-set2]

148 Kugler, C, Hastings, T., Lewis, H., "Internet Printing Protocol/1.1: Job and Printer Administrative
149 Operations", <draft-ietf-ipp-ops-set2-0102.txt>, [December 8, 1999](#)[July 19, 2000](#).

150 [ldap-printer]

151 Fleming, P., Jones, K., Lewis, H., McDonald, I., "Internet Printing Protocol (IPP): LDAP Schema
152 for Printer Services", <draft-ietf-ipp-ldap-printer-schema-0400.txt>, work in progress, [March 8,](#)
153 [December 20, 2000](#).

154 [RFC2565]

155 Herriot, R., Butler, S., Moore, P., Tuner, R., "Internet Printing Protocol/1.0: Encoding and
156 Transport", RFC 2565, April 1999.

157 [RFC2566]

158 R. deBry, T. Hastings, R. Herriot, S. Isaacson, P. Powell, "Internet Printing Protocol/1.0: Model and
159 Semantics", RFC 2566, April 1999.

160 [RFC2910]

161 Herriot, R., Butler, S., Moore, P., Turner, R., "Internet Printing Protocol/1.1: Encoding and
162 Transport", RFC 2910, September 2000.

163 [RFC2911]

164 R. deBry, T. Hastings, R. Herriot, S. Isaacson, P. Powell, "Internet Printing Protocol/1.0: Model and
165 Semantics", RFC 2911, September 2000.

166 [svrloc-printer]

167 St. Pierre, P., Isaacson, S., McDonald, I., "Definition of the Printer Abstract Service Type v2.0",
168 <draft-ietf-svrloc-printer-scheme-06.txt>, work in progress, March 8, 2000.

169

16 Appendix A: Allowed Values for Set-Printer-Attributes and Set-Job-Attributes requests

This appendix is a normative part of this document and contains a table of all IPP/1.1 attributes. Each row contains:

- an attribute and
- the values allowed in the Set-Printer-Attributes or Set-Job-Attributes request for the attribute. The entry in each cell is the name (first few words) of each item below 1, 2, 3, 4a-g, and 5.

The allowed values include the following cases:

1. **READ-ONLY:** the Set-Printer-Attributes or Set-Job-Attributes operation **MUST NOT** change this attribute and **MUST** reject the entire operation (see section 7.1).
2. **Any of "xxx-supported":** the Set-Printer-Attributes or Set-Job-Attributes operation accepts values that are allowed according to the IPP/1.1 rules for validating the value(s) of an "xxx" Printer or Job attribute against the value(s) of the corresponding "xxx-supported" Printer attribute. Table 5 summarizes those validation rules depending on each attribute syntax and value of an "xxx" attribute supplied in the request and that of the corresponding "xxx-supported" Printer attribute. The "xxx-supported" attribute syntax type and value(s) are obtained from a Get-Printer-Supported-Values response (see the tables in this Appendix).

Table 5 - Validation rules for 'Any of "xxx-supported" '

Type of "xxx" value to be set	Type of "xxx-supported" value	Validates if:
integer	rangeOfInteger	each value is in one of the "xxx-supported" ranges
uri	uriScheme	each uri scheme matches one of the "xxx-supported" schemes
any	boolean	if the boolean "xxx-supported" is 'true'
any	same type	each value matches an "xxx-supported" value of the same type

For additional non-normative explanatory information see section 3.1.2.3 of the "Internet Printing Protocol/1.1: Implementer's Guide" [ipp-iig]).

3. **From Get-Printer-Supported-Values:** the Set-Printer-Attributes operation accepts values that are allowed according to the IPP/1.1 rules for validating the value(s) of an "xxx" Printer attribute against the value(s) of the corresponding "xxx-supported" Printer attribute. Table 6 summarizes those validation rules depending on each attribute syntax and value of an "xxx" attribute supplied in the request and that of the corresponding "xxx-supported" Printer attribute. The "xxx-supported"

197 attribute syntax type and attribute value(s) are obtained from a Get-Printer-Supported-Values
 198 response (see Appendix B: Attributes returned from Get-Printer-Supported-Values below).

199 **Table 6 - Validation rules for 'From Get-Printer-Supported-Values'**

Type of "xxx" value to be set	Type of "xxx-supported" value	Validates if:
integer	rangeOfInteger	each 'integer' value is in one of the "xxx-supported" ranges
uri	uriScheme	the uri scheme of each value matches one of the "xxx-supported" schemes
any	boolean	if the boolean "xxx-supported" is 'true'
name	'admin-define' out-of-band value	any 'name' value matches
any	same type	each value matches an "xxx-supported" value of the same type

200

201 For additional non-normative explanatory information see section 3.1.2.3 of the "Internet Printing
 202 Protocol/1.1: Implementer's Guide" [ipp-iig]).

- 203 4. Any value of the proper attribute syntax: the Set-Printer-Attributes or Set-Job-Attributes operation
 204 accepts any value of the specified attribute syntax. The attribute syntaxes supported are
 205 enumerated below.
- 206 a. Any text(127)
 - 207 b. Any name(127)
 - 208 c. Any uri
 - 209 d. Any boolean
 - 210 e. Any positive integer
 - 211 f. Any dateTime
 - 212 g. 1setOf any uri
- 213
- 214 5. Combination of 'Any of "xxx-supported"' or 'Any name'.

215 If a Printer implementation doesn't want to allow setting values indicated in this Appendix as "any xxx",
 216 it can make the value be not-settable.

217

Table 7 - Values allowed for Job Template Attributes in the Set-Job-Attributes Operation

Job Template Attributes	Values allowed for Set
job-priority (integer(1:100))	Any of "xxx-supported"
job-hold-until (type3 keyword name (MAX))	Any of "xxx-supported"
job-sheets (type3 keyword name(MAX))	Any of "xxx-supported"
multiple-document-handling (type2 keyword)	Any of "xxx-supported"
copies (integer(1:MAX))	Any of "xxx-supported"
finishings (1setOf type2 enum)	Any of "xxx-supported"
page-ranges (1setOf rangeOfInteger (1:MAX))	Any of "xxx-supported"
sides (type2 keyword)	Any of "xxx-supported"
number-up (integer(1:MAX))	Any of "xxx-supported"
orientation-requested (type2 enum)	Any of "xxx-supported"
media (type3 keyword name(MAX))	Any of "xxx-supported"
printer-resolution (resolution)	Any of "xxx-supported"
print-quality (type2 enum)	Any of "xxx-supported"

218

Table 8 - Values allowed for Job Description Attributes in the Set-Job-Attributes Operation

Job Description Attributes	Values allowed for Set
job-uri (uri)	READ-ONLY
job-id (integer(1:MAX))	READ-ONLY
job-printer-uri (uri)	READ-ONLY
job-more-info (uri)	READ-ONLY
job-name (name(MAX))	Any name(MAX)
job-originating-user-name (name(MAX))	READ-ONLY
job-state (type1 enum)	READ-ONLY
job-state-reasons (1setOf type2 keyword)	READ-ONLY
job-state-message (text(MAX))	READ-ONLY
job-detailed-status-messages (1setOf text(MAX))	READ-ONLY
job-document-access-errors (1setOf text(MAX))	READ-ONLY
number-of-documents (integer(0:MAX))	READ-ONLY
output-device-assigned (name(127))	READ-ONLY
time-at-creation (integer(MIN:MAX))	READ-ONLY
time-at-processing (integer(MIN:MAX))	READ-ONLY
time-at-completed (integer(MIN:MAX))	READ-ONLY
job-printer-up-time (integer(1:MAX))	READ-ONLY
date-time-at-creation (dateTime)	READ-ONLY
date-time-at-processing (dateTime)	READ-ONLY
date-time-at-completed (dateTime)	READ-ONLY
number-of-intervening-jobs (integer(0:MAX))	READ-ONLY
job-message-from-operator (text(127))	Any text(127)
job-k-octets (integer(0:MAX))	READ-ONLY
job-impressions (integer(0:MAX))	READ-ONLY
job-media-sheets (integer(0:MAX))	READ-ONLY
job-k-octets-processed (integer(0:MAX))	READ-ONLY
job-impressions-completed (integer(0:MAX))	READ-ONLY
job-media-sheets-completed (integer(0:MAX))	READ-ONLY
attributes-charset (charset)	READ-ONLY
attributes-natural-language (naturalLanguage)	READ-ONLY

221
222**Table 9 - Values allowed for Printer Job Template Attributes in the Set-Printer-Attributes Operation**

Printer Job Template Attributes	Values allowed for Set
job-priority-default (integer(1:100))	Any of "xxx-supported"
job-hold-until-default (type3 keyword name (MAX))	Any of "xxx-supported"
job-sheets-default (type3 keyword name(MAX))	Any of "xxx-supported"
multiple-document-handling-default (type2 keyword)	Any of "xxx-supported"
copies-default (integer(1:MAX))	Any of "xxx-supported"
finishings-default (1setOf type2 enum)	Any of "xxx-supported"
sides-default (type2 keyword)	Any of "xxx-supported"
number-up-default (integer(1:MAX))	Any of "xxx-supported"
orientation-requested-default (type2 enum)	Any of "xxx-supported"
media-default (type3 keyword name(MAX))	Any of "xxx-supported"
printer-resolution-default (resolution)	Any of "xxx-supported"
print-quality-default (type2 enum)	Any of "xxx-supported"
job-priority-supported (integer(1:100))	From Get-Printer-Supported-Values
job-hold-until-supported (1setOf(type3 keyword name (MAX)))	From Get-Printer-Supported-Values
job-sheets-supported (1setOf(type3 keyword name(MAX)))	From Get-Printer-Supported-Values
multiple-document-handling-supported (1setOf type2 keyword)	From Get-Printer-Supported-Values
copies-supported (rangeOfInteger(1:MAX))	From Get-Printer-Supported-Values
finishings-supported (1setOf type2 enum)	From Get-Printer-Supported-Values
page-ranges-supported (boolean)	From Get-Printer-Supported-Values
sides-supported (1setOf type2 keyword)	From Get-Printer-Supported-Values
number-up-supported (1setOf (integer(1:MAX) rangeOfInteger(1:MAX)))	From Get-Printer-Supported-Values
orientation-requested-supported (1setOf type2 enum)	From Get-Printer-Supported-Values
media-supported (1setOf (type3 keyword name(MAX)))	From Get-Printer-Supported-Values
printer-resolution-supported (1setOf resolution)	From Get-Printer-Supported-Values
print-quality-supported (1setOf type2 enum)	From Get-Printer-Supported-Values
media-ready (type3 keyword name(MAX))	From Get-Printer-Supported-Values

223
224
225**Table 10 - Values allowed for Printer Description Attributes in the Set-Printer-Attributes Operation**

Printer Description Attributes	Values allowed for Set
printer-uri-supported (1setOf uri)	READ-ONLY
uri-authentication-supported (1setOf type2 keyword)	READ-ONLY
uri-security-supported (1setOf type2 keyword)	READ-ONLY
printer-xri-supported (1setOf collection) member attributes:	
xri-uri (uri)	any uriScheme of "xri-uri-scheme-supported" from Get-Printer-Attributes
xri-authentication (1setOf type2 keyword)	any keyword of "xri-authentication-supported" from Get-Printer-Attributes
xri-security (1setOf type2 keyword)	any keyword of "xri-security-supported" from Get-Printer-Attributes
xri-uri-scheme-supported (1setOf uriScheme)	READ-ONLY
xri-authentication-supported (1setOf type2 keyword)	READ-ONLY
xri-security-supported (1setOf type2 keyword)	READ-ONLY
printer-name (name(127))	Any name(127)
printer-location (text(127))	Any text(127)
printer-info (text(127))	Any text(127)
printer-more-info (uri)	Any uri
printer-driver-installer (uri)	Any uri
printer-make-and-model (text(127))	Any text(127)
printer-more-info-manufacturer (uri)	Any uri
printer-state (type1 enum)	READ-ONLY
printer-state-reasons (1setOf type2 keyword)	READ-ONLY
printer-state-message (text(MAX))	READ-ONLY
ipp-versions-supported (1setOf type2 keyword)	From Get-Printer-Supported-Values
operations-supported (1setOf type2 enum)	From Get-Printer-Supported-Values
multiple-document-jobs-supported (boolean)	From Get-Printer-Supported-Values
charset-configured (charset)	Any of "xxx-supported", use "charset-supported"
charset-supported (1setOf charset)	From Get-Printer-Supported-Values
natural-language-configured (naturalLanguage)	Any of "xxx-supported", use "generated-natural-language-supported"

Printer Description Attributes	Values allowed for Set
generated-natural-language-supported (1setOf naturalLanguage)	From Get-Printer-Supported-Values
document-format-default (mimeMediaType)	Any of "xxx-supported"
document-format-supported (1setOf mimeMediaType)	From Get-Printer-Supported-Values
printer-is-accepting-jobs (boolean)	READ-ONLY
queued-job-count (integer(0:MAX))	READ-ONLY
printer-message-from-operator (text(127))	Any text(127)
color-supported (boolean)	From Get-Printer-Supported-Values
reference-uri-schemes-supported (1setOf uriScheme)	From Get-Printer-Supported-Values
pdl-override-supported (type2 keyword)	From Get-Printer-Supported-Values
printer-up-time (integer(1:MAX))	READ-ONLY
printer-current-time (dateTime)	Any dateTime **
multiple-operation-time-out (integer(1:MAX))	any positive integer
compression-supported (1setOf type3 keyword)	From Get-Printer-Supported-Values
job-k-octets-supported (rangeOfInteger(0:MAX))	From Get-Printer-Supported-Values
job-impressions-supported (rangeOfInteger(0:MAX))	From Get-Printer-Supported-Values
job-media-sheets-supported (rangeOfInteger(0:MAX))	From Get-Printer-Supported-Values
pages-per-minute (integer(0:MAX))	READ-ONLY
pages-per-minute-color (integer(0:MAX))	READ-ONLY
printer-settable-attributes-supported (1setOf type2 keyword)	From Get-Printer-Supported-Values
job-settable-attributes-supported (1setOf type2 keyword)	From Get-Printer-Supported-Values
document-format-varying-attributes (1setOf type2 keyword)	READ-ONLY
printer-message-time (integer(MIN:MAX))	READ-ONLY
printer-message-date-time(dateTime)	READ-ONLY

226

227

228

** - The "printer-current-time" (dateTime) attribute is settable in order to allow an administrator to correct an incorrect dateTime or time zone.

229

17 Appendix B: Attributes returned from Get-Printer-Supported-Values

230

231

This Appendix is a normative part of this document and lists all the attributes that are possible for an implementation to return in a Get-Printer-Supported-Values response, i.e., all the "xxx-supported"

232 attributes that can be supplied in a Set-Printer-Attributes request. READ-ONLY attributes MUST
 233 NOT be returned in a Get-Printer-Supported-Values response and are indicated in the tables as "READ-
 234 ONLY - MUST NOT be returned."

235 For the following attributes, the value allowed by the Set-Printer-Attributes operation MUST be a
 236 single integer value in the range specified by the value returned by the Get-Printer-Supported-Values
 237 operation.

238 **Table 11 - Printer Job Template Attributes returned from Get-Printer-Supported-Values**

Printer Job Template Attributes	Values Returned
job-priority-supported (integer(1:100))	rangeOfInteger(1:100)

239 For the following attributes, the value allowed by the Set-Printer-Attributes operation MUST be a
 240 single rangeOfInteger value whose bounds do not exceed those of the range specified by the value
 241 returned by the Get-Printer-Supported-Values operation.
 242

243 **Table 12 - Printer Job Template Attributes returned from Get-Printer-Supported-Values**

Printer Job Template Attributes	Values Returned
copies-supported (rangeOfInteger(1:MAX))	rangeOfInteger(1:MAX)

244
 245 The following table has the same criteria as the last, but is for Printer Description attributes.

246 **Table 13 - Printer Description Attributes returned from Get-Printer-Supported-Values**

Printer Description Attributes	Values allowed for Set
job-k-octets-supported (rangeOfInteger(0:MAX))	rangeOfInteger(0:MAX)
job-impressions-supported (rangeOfInteger(0:MAX))	rangeOfInteger(0:MAX)
job-media-sheets-supported (rangeOfInteger(0:MAX))	rangeOfInteger(0:MAX)

247 For the following attributes, the value allowed by the Set-Printer-Attributes operation MUST be one or
 248 more integers and rangeOfInteger values, such that the integer values described by these integers and
 249 rangeOfInteger is the same as or a subset of the integers described by the integers and rangeOf Integer
 250 of value returned by the Get-Printer-Supported-Values operation.
 251

252 **Table 14 - Printer Job Template Attributes returned from Get-Printer-Supported-Values**

Printer Job Template Attributes	Values Returned
number-up-supported (1setOf (integer(1:MAX) rangeOfInteger(1:MAX)))	1setOf (integer(1:MAX) rangeOfInteger(1:MAX))

253

254 For the following attributes, the value allowed by the Set-Printer-Attributes operation MUST be one or
 255 more values, where each such value matches a value returned by the Get-Printer-Supported-Values
 256 operation. A keyword, enum, boolean, charset, naturalLanguage, uriScheme, mimeType or
 257 resolution value matches if it is equal. For Job Template attributes with the attribute syntax 'type3
 258 keyword | name', any 'name' attribute syntax value matches the 'admin-define' out-of-band value, if the
 259 implementation allows the administrator to set any name values for the attribute.

260 **Table 15 - Printer Job Template Attributes returned from Get-Printer-Supported-Values**

Printer Job Template Attributes	Values Returned
job-hold-until-supported (1setOf(type3 keyword name (MAX)))	1setOf (type3 keyword 'admin-define')
job-sheets-supported (1setOf(type3 keyword name(MAX)))	1setOf (type3 keyword 'admin-define')
multiple-document-handling-supported (1setOf type2 keyword)	1setOf type2 keyword
finishings-supported (1setOf type2 enum)	1setOf type2 enum
page-ranges-supported (boolean)	1setOf boolean **
sides-supported (1setOf type2 keyword)	1setOf type2 keyword
orientation-requested-supported (1setOf type2 enum)	1setOf type2 enum
media-supported (1setOf (type3 keyword name(MAX)))	1setOf (type3 keyword 'admin-define')
printer-resolution-supported (1setOf resolution)	1setOf resolution
print-quality-supported (1setOf type2 enum)	1setOf type2 enum

261 ** Note: the Get-Printer-Supported-Values returns a '1setOf boolean' so that all possible values are
 262 indicated, while Get-Printer-Attributes returns only a single 'boolean' value.

263 The following table has the same criteria as the last, but is for Printer Description attributes.

264

Table 16 - Printer Description Attributes returned from Get-Printer-Supported-Values

Printer Description Attributes	Values allowed for Set
printer-uri-supported (1setOf uri)	READ-ONLY - MUST NOT be returned
uri-authentication-supported (1setOf type2 keyword)	READ-ONLY - MUST NOT be returned
uri-security-supported (1setOf type2 keyword)	READ-ONLY - MUST NOT be returned
xri-printer-supported (1setOf collection)	MUST NOT be returned; see next three attributes returned with Get-Printer-Attributes:
xri-uri-scheme-supported (1setOf uriScheme)	READ-ONLY - MUST NOT be returned
xri-authentication-supported (1setOf type2 keyword)	READ-ONLY - MUST NOT be returned
xri-security-supported (1setOf type2 keyword)	READ-ONLY - MUST NOT be returned
ipp-versions-supported (1setOf type2 keyword)	1setOf type2 keyword
operations-supported (1setOf type2 enum)	1setOf type2 keyword
multiple-document-jobs-supported (boolean)	1setOf boolean **
charset-supported (1setOf charset)	1setOf charset
generated-natural-language-supported (1setOf naturalLanguage)	1setOf naturalLanguage
document-format-supported (1setOf mimeType)	1setOf mimeType
color-supported (boolean)	1setOf boolean **
reference-uri-schemes-supported (1setOf uriScheme)	1setOf uriScheme
pdl-override-supported (type2 keyword)	1setOf type2 keyword **
compression-supported (1setOf type3 keyword)	1setOf type3 keyword
printer-settable-attributes-supported (1setOf type2 keyword)	1setOf type2 keyword
job-settable-attributes-supported (1setOf type2 keyword)	1setOf type2 keyword

265

** Note: the Get-Printer-Supported-Values returns a '1setOf X' so that all possible values are indicated, while Get-Printer-Attributes returns only a single 'X' value.

266

267

18 Appendix C: Description of the Base IPP Documents

268

The base set of IPP documents includes:

269

[Design Goals for an Internet Printing Protocol \[RFC2567\]](#)

270

[Rationale for the Structure and Model and Protocol for the Internet Printing Protocol \[RFC2568\]](#)

271

[Internet Printing Protocol/1.1: Model and Semantics \[RFC2911\]](#)

272

[Internet Printing Protocol/1.1: Encoding and Transport \[RFC2910\]](#)

273

[Internet Printing Protocol/1.1: Implementer's Guide \[IPP-IIG\]](#)

Mapping between LPD and IPP Protocols [RFC2569]

The "Design Goals for an Internet Printing Protocol" document takes a broad look at distributed printing functionality, and it enumerates real-life scenarios that help to clarify the features that need to be included in a printing protocol for the Internet. It identifies requirements for three types of users: end users, operators, and administrators. It calls out a subset of end user requirements that are satisfied in IPP/1.0 [RFC2566, RFC2565]. A few OPTIONAL operator operations have been added to IPP/1.1 [RFC2911, RFC2910].

The "Rationale for the Structure and Model and Protocol for the Internet Printing Protocol" document describes IPP from a high level view, defines a roadmap for the various documents that form the suite of IPP specification documents, and gives background and rationale for the IETF IPP working group's major decisions.

The "Internet Printing Protocol/1.1: Model and Semantics" document describes a simplified model with abstract objects, their attributes, and their operations. The model introduces a Printer and a Job. The Job supports multiple documents per Job. The model document also addresses how security, internationalization, and directory issues are addressed.

The "Internet Printing Protocol/1.1: Encoding and Transport" document is a formal mapping of the abstract operations and attributes defined in the model document onto HTTP/1.1 [RFC2616]. It also defines the encoding rules for a new Internet MIME media type called "application/ipp". This document also defines the rules for transporting over HTTP a message body whose Content-Type is "application/ipp". This document defines the 'ipp' scheme for identifying IPP printers and jobs.

The "Internet Printing Protocol/1.1: Implementer's Guide" document gives insight and advice to implementers of IPP clients and IPP objects. It is intended to help them understand IPP/1.1 and some of the considerations that may assist them in the design of their client and/or IPP object implementations. For example, a typical order of processing requests is given, including error checking. Motivation for some of the specification decisions is also included.

The "Mapping between LPD and IPP Protocols" document gives some advice to implementers of gateways between IPP and LPD (Line Printer Daemon) implementations.

19 Appendix **DC**: Full Copyright Statement

Copyright (C) The Internet Society (1998,1999,2000,2001). All Rights Reserved

This document and translations of it may be copied and furnished to others, and derivative works that comment on or otherwise explain it or assist in its implementation may be prepared, copied, published and distributed, in whole or in part, without restriction of any kind, provided that the above copyright notice and this paragraph are included on all such copies and derivative works. However, this document itself may not be modified in any way, such as by removing the copyright notice or references to the Internet Society or other Internet organizations, except as needed for the purpose of developing Internet standards in which case the procedures for copyrights defined in the Internet Standards process must be followed, or as required to translate it into languages other than English.

312 The limited permissions granted above are perpetual and will not be revoked by the Internet Society or
313 its successors or assigns.

314 This document and the information contained herein is provided on an "AS IS" basis and THE
315 INTERNET SOCIETY AND THE INTERNET ENGINEERING TASK FORCE DISCLAIMS ALL
316 WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY
317 WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY
318 RIGHTS OR ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A
319 PARTICULAR PURPOSE.

320 **Acknowledgement**

321 Funding for the RFC Editor function is currently provided by the Internet Society.